

---

# Notes When Using the TA720

---

To load measured data of the TA720, the TA720 ROM version must be 1.02 or later. You can check the ROM version of the TA720 in the Version Information dialog box that appears by pressing Utility followed by Version on the TA720.

If the ROM version your TA720 is 1.01, upgrade the TA720 firmware using the TA720 firmware floppy disk according to the following procedure.

---

## **CAUTION**

- If you turn off the power to the TA720 while the firmware is being upgraded, the TA720 may fail to start.
  - If you perform the following procedure and the TA720 no longer starts or the operation becomes abnormal, contact your nearest YOKOGAWA dealer.
- 

### **Upgrading the TA720 Firmware**

#### **Preparations before Upgrading**

- If you wish to keep the setup data that you are currently using, save the setup data to a floppy disk or a PC card. For a description of the save procedure, see section 11.4 in the *TA720 User's Manual (IM 704510-01E)*.
- If the setup data is stored to the internal memory of the TA720 and you wish to save the data, recall the setup data first, then save the setup data to a floppy disk or PC card. For a description of the recall procedure of the setup data and the save procedure, see sections 10.2 and 11.4, respectively, in the *TA720 User's Manual*.

#### **Procedure**

1. With the power turned OFF, insert the floppy disk that came with the package into the TA720 floppy drive.
2. Turn ON the power while holding down the **SHIFT** key.  
The TA720 upgrade starts automatically.  
Leave the power turned ON and wait until "success" appears on the screen.
3. Turn OFF the power to the TA720 once and turn in back ON while holding down the **RESET** key.
4. Check that the ROM version of the TA720 in the Version Information dialog box that appears by pressing Utility followed by Version on the TA720 is 1.02 or later.

#### **Note**

---

For a description of recalling the setup data that was saved to a floppy disk or a PC card, see section 11.4 in the *TA720 User's Manual*.

---